

5. Functional Features:

The operation is simple and user-friendly, with dimming that eliminates flickering and shaking. It is suitable for photography, videography, and television studios where strict lighting requirements are needed.

LED Stage Lighting Equipment User Manual

LED imaging lamp



operating instruction

Read carefully before use

1. Illustration section:



A. Function key B. Plus key C. Minus key D. Confirm key



A B C D

Instructions: Pressing function key A will display various effects in sequence, with the first two digits shown on the digital display.

Represents the current function (refer to the function table). The last two digits indicate the address of the function.

Code or speed parameters. Press B or C to modify the parameter values. Press D to confirm.

2. LED display window function comparison table (Select all functions and press D to confirm)

NO.	Show	function declaration
1	A001	Address code (001-512) for B and C keys: Add or subtract the address code value
2	1CH/2CH	Channel selection (1 channel, 2 channels) Addition and subtraction of B and C bonds
3	EE95	Gradient (00-99) B, C key modification speed

4	o255	Dimming, (000—255) B, C key color modification
---	------	---

3.DMX512 channel description (1 channel)

NO.	function	function declaration
Channel 1	total dimming	Total dimming, linear dimming, from dark to bright

4. Description of DMX512 channels (2 channels)

NO.	function	function declaration
Channel 1	total dimming	Total dimming, linear dimming, from dark to bright
Channel 2	strobe flash	Flicker, 0-100%